

WIRELESS DMX TRANSMITTER

ART3



The Wireless DMX Receiver & Transmitter is a versatile product that can be used in several ways to form large wireless lighting setups. Use it as a plain DMX transmitter to bridge the gap between a DMX controller and its lamps. Connect it to third party DMX lamps and use the Astera RF Remote Control to control them. Connect it to a DMX light control system so it can control color and intensity of any Astera lamp.

TECHNICAL SPECIFICATIONS

Working Voltage:	Input-110-240V, 50/60Hz
Battery:	no
Output Socket:	2 x XLR 3-pole (DMX in & out)
DMX Capability:	DMX-512 in/out
Channels:	512
Wireless Module:	868MHz sender/receiver (USA version: 902-928MHz sender/receiver)
Range:	300m (330yd)
Control Pad:	5 multi-functional buttons and LCD display for basic operation
Environment:	Indoor and dry outdoor
Unit Size:	L160mm x W105mm x H50mm (L6.3" x W4.1" x H2.0")
Weight:	0.850kg (1.9lb)
Casting Material:	Aluminum
Modes:	Sending, receiving, transmitting
Functions:	Group addressing, Chain addressing, Type addressing, Serial Number addressing
Included Accessories:	Power Cord for the integrated power supply

SUITABLE CONTROLLERS



ARC2



DMX controllers

SUITABLE LAMPS



AL1



AL3



AL5



AL6



AL7



AL7-W



AL8